Specifications



Eaton 107206

Eaton xEffect SASY 60i Enclosures Switch- & Controlgear Enclosure. Busbar adapter, 3p, for NZM3, 630A, UL508

General specifications	
PRODUCT NAME	Eaton xEffect SASY 60i MCCB adapter
CATALOG NUMBER	107206
MODEL CODE	NZM3-XAD630
EAN	4015081069699
PRODUCT LENGTH/DEPTH	272 mm
PRODUCT HEIGHT	35 mm
PRODUCT WIDTH	140 mm
PRODUCT WEIGHT	2.342 kg
COMPLIANCES	UL CSA09 (refer to approbation report) IEC 60439-1 UL508A CE marking CSA-C22.2 No. 14 RoHS conform
CERTIFICATIONS	North America (UL listed, CSA certified) CSA (File No. 236217) UL (File No. E300273) UL (Category Control Number NMTR, NMTR7) CSA (Class No. 3211-37)
CATALOG NOTES	For surface mounting on flat copper busbars 12 – 30 x 5 – 10, double T and triple T profile

Additional information

FEATURES	Self-extinguishing acc. UL 94
FUNCTIONS	Busbar adapters for NZM Current limiting circuit breaker, refer to approbation report Component adapter for circuit breakers and switch-disconnector
SUITABLE FOR	Surface mounting on flat copper busbars 12 – 30 x 5 – 10, double T and triple T profile
USED WITH	N(S)3 NZM3 PN3 Feeder circuits Busbar adapters for NZM 60 mm system

Delivery program

NOMINAL CURRENT	630 A
NUMBER OF POLES	Three-pole
TYPE	• 60 mm system • Busbar adapters for NZM

Design verification as per IEC/EN 61439 - technical data

EQUIPMENT HEAT DISSIPATION, CURRENT-DEPENDENT PVID	61.8 W
TEMPERATURE RESISTANCE	Up to 120 °C

Technical data - electrical

CREEPAGE RESISTANCE	CTI 200
ELECTRIC CONNECTION TYPE	Other
RATED OPERATION CURRENT (IE)	630 A
VOLTAGE RATING (UL CSA 13)	Max. 600 V AC
VOLTAGE RATING AT AC	690 V AC

Technical data - mechanical

ADAPTER WIDTH	140 mm
BUSBAR ADAPTER WIDTH	140 mm
BUSBAR DISTANCE	60 mm
BUSBAR THICKNESS - MAX	10 mm
BUSBAR THICKNESS - MIN	5 mm
DEGREE OF PROTECTION	Feeder circuits
MOUNTING RAIL ARMAMENT	None
RAIL WIDTH	30 mm

Resources

BROCHURES	eaton-xeffect-sasy60i-customer-success-story-css-wagner-mueller-en-us.pdf
CERTIFICATION REPORTS	eaton-xeffect-sasy-60i-declaration-of-conformity.pdf
DRAWINGS	eaton-control-panels-xeffect-sasy-busbar-adapter-dimensions.eps eaton-circuit-breaker-busbar-xeffect-sasy-busbar-adapter-3d-drawing.eps
INSTALLATION INSTRUCTIONS	eaton-xeffect-sasy-60i-installation-leaflet-nzm3-il01502147-z.pdf
MCAD MODEL	eaton-busbar-adapters-mcad-drawings-nzm3-xad630.dwg nzm3_xad630.stp
TECHNICAL DATA SHEETS	eaton-xeffect-sasy-60i-fk4300-1167gb-en-us.pdf

PROJECT NAME:	
PROJECT NUMBER:	
PREPARED BY:	
DATE:	

Eaton Corporation plc Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2026 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.