Specifications



Eaton 248439

Eaton Distribution board accessory, Shunt release, 110-415V, 1HP

General specifications	
PRODUCT NAME	Eaton distribution board accessory
CATALOG NUMBER	248439
MODEL CODE	ZP-ASA/230
EAN	4015082484392
PRODUCT LENGTH/DEPTH	80 mm
PRODUCT HEIGHT	75 mm
PRODUCT WIDTH	26.2 mm
PRODUCT WEIGHT	0.087 kg
COMPLIANCES	RoHS conform
CERTIFICATIONS	EN45545-2 IEC 61373

Product specifications

USED WITH	Shunt releases Accessory for combined residual current/power circuit breaker Accessory Accessory for miniature circuit breaker
ACCESSORY/SPARE PART TYPE	Shunt release
MOUNTING METHOD	For fitting on left to: FAZ, FRBmM-1N, Z-MS
ADDITIONAL EQUIPMENT REQUIRED	Shunt release (for power circuit breaker)
AMBIENT OPERATING TEMPERATURE - MAX	75 °C
AMBIENT OPERATING TEMPERATURE - MIN	-35 °C
ASSEMBLY WIDTH	1
NUMBER OF CONTACTS (CHANGE-OVER CONTACTS)	0
NUMBER OF CONTACTS (NORMALLY CLOSED CONTACTS)	1
NUMBER OF CONTACTS (NORMALLY OPEN CONTACTS)	1
NUMBER OF POLES AT MAIN CONTACT UNIT - MAX	1
NUMBER OF SWITCHES (FAULT SIGNAL)	0
VOLTAGE TYPE	AC
FUNCTIONS	Shunt release (for power circuit breaker)
DEVICE FITTING	Other
TYPE	• Accessory • Accessory for combined residual current/power circuit breaker • Accessory for miniature circuit breaker
APPLICATION	Switchgear for industrial and advanced commercial applications
RATED OPERATIONAL VOLTAGE (UE) - MAX	230 V
SUITABLE FOR CURRENT OF MAIN CONTACT UNIT - MAX	2.1 A

Resources

DECLARATIONS OF CONFORMITY	eaton-distribution-parts-declaration-of-conformity-eu251409en.pdf
ECAD MODEL	ETN.ZP-ASA_230.edz
INSTALLATION INSTRUCTIONS	IL019163ZU
MCAD MODEL	faz_xaa.stp eaton-auxiliary-switches-mcad-drawings-faz-xaa.dwg
WIRING DIAGRAMS	eaton-wiring-diagram-asa.jpg

PROJECT NAME:	
PROJECT NUMBER:	
PREPARED BY:	
DATE:	

Eaton Corporation plc Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2026 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.